



**INTERCOM**  
How to pair 2 units **A**

With both units in Standby mode (led BLUE (6) flashing):

**1** On your unit press once the UP (2) button and then press once the MFB (1) button to activate the "SETUP" menu.

**2** Press three times the UP (2) button to select "INTERCOM DEVICE SEARCH" feature, press the MFB (1) until the beep to start the search.

**3** On the second unit (F5MC or F4MC or F3MC) press UP (2) button and then press once MFB (1) button to activate the "SETUP" menu.

**4** Press UP (2) button two times, the second MC unit will go in "PAIRING MODE".

**5** After few seconds the units will be paired, intercom connection will be automatically started (led BLUE (6) on). To stop the intercom communication press once MFB (1) button on one of the two units.

With both units in Standby mode (led BLUE (6) flashing):

**6** To start a conversation press the central button of unit 1.

**INTERCOM**  
How to pair 3 units **B**

Repeat step **A**, and then

**1** On your unit press once the UP (2) button and then press once the MFB (1) button to activate the "SETUP" menu.

**2** Press three times the UP (2) button to select "INTERCOM DEVICE SEARCH" feature, press the MFB (1) until the beep to start the search.

**3** On the third unit (F5MC or F4MC or F3MC) press UP (2) button and then press once MFB (1) button to activate the "SETUP" menu.

**4** Press UP (2) button two times, the third MC unit will go in "PAIRING MODE".

**5** After few seconds the units will be paired, intercom connection will be automatically started (led BLUE (6) on). To stop the intercom communication press once MFB (1) button on one of the two units.

With both units in Standby mode (led BLUE (6) flashing):

**6** To start a conversation press the central button of unit 1.

**INTERCOM**  
How to pair 4 units **C**

Repeat step **A** and step **B**, and then

**1** On the fourth unit press once the UP (2) button and then press once the MFB (1) button to activate the "SETUP" menu.

**2** Press three times the UP (2) button to select "INTERCOM DEVICE SEARCH" feature, press the MFB (1) until the beep to start the search.

**3** On the third unit (F5MC or F4MC or F3MC) press UP (2) button and then press once MFB (1) button to activate the "SETUP" menu.

**4** Press UP (2) button two times, the third MC unit will go in "PAIRING MODE".

**5** After few seconds the units will be paired, intercom connection will be automatically started (led BLUE (6) on). To stop the intercom communication press once MFB (1) button on one of the two units.

With both units in Standby mode (led BLUE (6) flashing):

**6** Start a conversation between three devices (1-2-3). Press the central button of unit 1.

**7** Press the central button of unit 4 to start add the fourth user to the conversation.

**INTERCOM**  
Anycom pairing (different brands) **D**

With both units in Standby mode (led BLUE (6) flashing):

**1** On your unit press once the UP (2) button and then press once the MFB (1) button to activate the "SETUP" menu.

**2** Press four times the UP (2) button to select "ANYCOM SEARCH" feature, press the MFB (1) until the beep to start the search.

**3** On the second NON Interphone device activate the search for another telephone; refer to the relative user manual if necessary.

**4** After few seconds the units will be paired, intercom connection will be automatically started (led BLUE (6) on). To stop the intercom communication press once MFB (1) button on one of the two units.

**SONG SHARING**  
How to share music from MP3 source **F**

With unit 1 on "music streaming" menu

**1** Press UP (2) button until the beep to start the song sharing with Interphone 1.

**2** Press UP (2) button until the beep to stop the song sharing with Interphone 1.

**PHONE / GPS**  
Pairing with an other Bluetooth device **E**

With both units in Standby mode (led BLUE (6) flashing):

**1** Start Bluetooth® service on mobile phone / GPS / MP3 player (check the device's user guide for more details).

**2** On your unit press once the UP (2) button and then press once the MFB (1) button to activate the "SETUP" menu.

**3** Press UP (2) button two times, the second MC unit will go in "PAIRING MODE".

**4** Start searching for new Bluetooth® devices on mobile phone / GPS / MP3 player.

**5** After few moments the device in searching mode will list "Interphone F5MC". Select it.

**6** If prompted for a PIN number, type "0000" (four times the zero number).

**7** F5MC vocal guide will confirm the successful pairing with the message "PAIRING SUCCESSFUL, CONNECTED TO PHONE". F5MC will go in Standby mode, the led BLUE (6) will flash twice, every three seconds.

**8** If the Bluetooth® device ask authorization to phonebook access, confirm.

If you want to pair a second device, repeat the pairing procedure from step 1.

**2** Press UP (2) button until the beep to stop the song sharing with Interphone 1.